

128GB Computer memory DDR4 for Gigabyte R182-NA0 LRDIMM



958,57 EUR

plus VAT

1.140,70 EUR

incl. VAT

en stock

<https://www.phs-memory.es>

Version: 29.08.2025 19:11

Your benefits

- ✓ verified quality memory
- ✓ 5 years warranty
Warranty details see last page
- ✓ 100% compatible
- ✓ free support on our hotline
- ✓ fast delivery

PHS-memory® - computer memory with 100% quality

- many years of IT competence
- Free support for optimal configuration and product selection
- High availability through professional warehouse management
- Fast delivery in throughout Europe
- Short response times and professional order processing due to full digitalization throughout the entire process with complete traceability
- Incoming goods inspection include checks of the DRAMs, PCBs and the programmed SPDs in order to exclude possible errors (Controlled BOM).
- PHS-memory® brand memories guarantee 100% compatibility to the specified system.
- PHS-memory® memories can be used together with existing memories in the device - depends on to the configuration rules of the system.
- The "fallback option" in the SPD of PHS-memory® allows DRAMs with higher clock rates to be operated together with older memory modules with lower clock rates within the system.
- Products with unique serial number for service and warranty
- Pre-sales and after-sales support by technically trained personnel

Memory Specification



Memory size	128GB
Memory technology	DDR4
ECC support	yes
JEDEC Norm	PC4-25600-L
DRAM Organization	8Gx4
Rank	4Rx4 (4DRx4 DDP)
Type	LRDIMM (ECC LR DIMM)
Number of pins	288 Pin DIMM
Memory data transfer rate	3200MHz @ CL22
Voltage	1,2 Volt
Speciality	DDP
Board dimensions	133,35 x 31,25 (LxB mm)
Operating temperature	0° C - 85° C
Storage temperature	-40° C - +95° C
RoHS compliant	yes
SKU	SP470491
EAN	4067488340208

Note: The module specified in this datasheet is one of several possible configurations available under this part number.
Some details may differ from the specifications described here and the illustration, but have no negative influence on the functionality.

System Specifications

The memory is 100% compatible with this system:

System manufacturer	Gigabyte
Device type	Server
Device family	Rack Server
Device series	R182 Serie
Device name	R182-NA0
Maximum memory*	8TB / 4TB according to manufacturer
Number of memory sockets	32

* The specifications for the maximum memory upgrade may differ from those of the manufacturer Gigabyte. Often the information given in the manual for the maximum memory upgrade is not up to date. New memory technologies, bios updates or newer software versions often allow the use of memory modules with a higher capacity than specified by the manufacturer with the same performance and stability.

Information on memory allocation

Information on memory configuration

The following technical specifications should be considered in advance:

- The system supports RDIMM and RDIMM 3DS (Registered DIMM) or LRDIMM and LRDIMM 3DS (Load Reduced DIMM) memory modules. Large memory capacities can be realised with LRDIMM 3DS modules.
- RDIMM and RDIMM 3DS memory modules cannot be operated together with LRDIMM and LRDIMM 3DS main memories.
- If a memory expansion is to be made with the already existing RAM memories, it must be checked which basic memory technology (RDIMM / LRDIMM) is available.
- When using a multiprocessor system, the memory slots should always be configured identically for each CPU.
- Memory slots without a processor may not be used.
- If memory modules are provided with higher speeds than specified by the system, the memory speed is automatically adjusted to the system specifications.

Maximum memory speed of possible CPUs

Xeon CPUs of the 3rd generation are offered in Bronze, Silver, Gold or Platinum. The different processor series also support different maximum memory speeds:

Xeon	CPU-series	max. Speed MHz	max. memory capacity je CPU	CPU xxxxH	CPU xxxxHL
Silver	4300	2666	6 TB		
Gold	5300	2933	6 TB	1,2 TB	4,5 TB
Gold	6300	3200	6 TB	1,2 TB	4,5 TB
Platinum	8300	3200	6 TB	1,2 TB	4,5 TB

Information on memory installation

- Turn off the system
- Remove the plug of the power supply unit (if connected)
- Remove the battery, according to the user manual of the system
- Always ground yourself before touching electronic components
- Protect the memory module from static voltages:
 - Do not touch the gold pins of the memory module
 - Only touch the sides of the memory module
 - Use a grounding strap and/or ESD glove if possible

General installation instructions are supplied by E-Mail.

Further memory options for Gigabyte R182-NA0

Size	SKU	Technology	Type	Number of pins	Brand	Reference no.
8GB	SP473619	DDR4	RDIMM (ECC Registered)	288 Pin DIMM	PHS-memory®	
16GB	SP381464	DDR4	RDIMM (ECC Registered)	288 Pin DIMM	PHS-memory®	
32GB	SP381465	DDR4	RDIMM (ECC Registered)	288 Pin DIMM	PHS-memory®	
64GB	SP381466	DDR4	RDIMM (ECC Registered)	288 Pin DIMM	PHS-memory®	
64GB	SP381462	DDR4	LRDIMM (ECC LR DIMM)	288 Pin DIMM	PHS-memory®	
128GB	SP470491	DDR4	LRDIMM (ECC LR DIMM)	288 Pin DIMM	PHS-memory®	
128GB	SP473618	DDR4	LRDIMM (ECC LR DIMM) 3DS	288 Pin DIMM	PHS-memory®	
128GB	SP381463	DDR4	RDIMM (ECC Registered) 3DS	288 Pin DIMM	PHS-memory®	
256GB	SP470493	DDR4	RDIMM (ECC Registered) 3DS	288 Pin DIMM	PHS-memory®	
256GB	SP470492	DDR4	LRDIMM (ECC LR DIMM) 3DS	288 Pin DIMM	PHS-memory®	

PHS-memory® warranty

Every PHS-memory® is equipped with a 5-years-warranty of perfect operation. If the RAM module is defective or fails within 5 years of purchase when used properly, you will receive an appropriate RAM module free of charge. If a suitable memory module is no longer available, we will refund the purchase price.

For more information on warranty and service please visit <https://www.phs-memory.es/-W5Y>



Contact Information

PHS-electronic gmbh
- www.phs-memory.es -
Karl-Götz-Str. 5
97424 Schweinfurt
Alemania

Phone: +49 9721 784678
E-Mail: info@phs-memory.es
Web: www.phs-memory.es

All information without guarantee. Technical changes and errors excepted. You can find current price information in our online shop at <https://www.phs-memory.es>