

# 16GB Computer memory DDR4 for Gigabyte R182-N20 RDIMM





# Your benefits ✓ verified quality memory ✓ 5 years warranty Warranty details see last page ✓ 100% compatible ✓ free support on our hotline ✓ fast delivery

# PHS-memory® - computer memory with 100% quality

- many years of IT competence
- Free support for optimal configuration and product selection
- High availability through professional warehouse management
- Fast delivery in throughout Europe
- Short response times and professional order processing due to full digitalization throughout the entire process with complete traceability
- Incoming goods inspection include checks of the DRAMs, PCBs and the programmed SPDs in order to exclude possible errors (Controlled BOM).
- PHS-memory® brand memories guarantee 100% compatibility to the specified system.
- PHS-memory® memories can be used together with existing memories in the device depends on to the configuration rules of the system.
- The "fallback option" in the SPD of PHS-memory® allows DRAMs with higher clock rates to be operated together with older memory modules with lower clock rates within the system.
- Products with unique serial number for service and warranty
- Pre-sales and after-sales support by technically trained personnel



# Memory Specification



Memory size	16GB
Memory technology	DDR4
ECC support	yes
JEDEC Norm	PC4-25600-R
Туре	RDIMM (ECC Registered)
Number of pins	288 Pin DIMM
Memory data transfer rate	3200MHz @ CL22
Voltage	1,2 Volt
Speciality	-
Board dimensions	133,35 x 31,25 (LxB mm)
Operating temperature	0° C - 85° C
Storage temperature	-40° C - +95° C
RoHS compliant	yes
SKU	SP381459
EAN	4064578444921

Note: The module specified in this datasheet is one of several possible configurations available under this part number.

Some details may differ from the specifications described here and the illustration, but have no negative influence on the functionality.



# System Specifications

The memory is 100% compatible with this sytem:

System manufacturer	Gigabyte
Device type	Server
Device family	Rack Server
Device series	R182 Serie
Device name	R182-N20
Maximum memory*	8TB / 4TB according to manufacturer
Number of memory sockets	32

<sup>\*</sup> The specifications for the maximum memory upgrade may differ from those of the manufacturer Gigabyte. Often the information given in the manual for the maximum memory upgrade is not up to date. New memory technologies, bios updates or newer software versions often allow the use of memory modules with a higher capacity than specified by the manufacturer with the same performance and stability.

# Information on memory allocation

### Information on memory configuration

The following technical specifications should be considered in advance:

- The system supports RDIMM and RDIMM 3DS (Registered DIMM) or LRDIMM and LRDIMM 3DS (Load Reduced DIMM) memory modules. Large memory capacities can be realised with LRDIMM 3DS modules.
- RDIMM and RDIMM 3DS memory modules cannot be operated together with LRDIMM and LRDIMM 3DS main memories.
- If a memory expansion is to be made with the already existing RAM memories, it must be checked which basic memory technology (RDIMM / LRDIMM) is available.
- When using a multiprocessor system, the memory slots should always be configured identically for each CPU.
- Memory slots without a processor may not be used.
- If memory modules are provided with higher speeds than specified by the system, the memory speed is automatically adjusted to the system specifications.

#### Maximum memory speed of possible CPUs

Xeon CPUs of the 3nd generation are offered in Bronze, Silver, Gold or Platinum. The different processor series also support different maximum memory speeds:

Xeon	CPU-series	max. Speed MHz	max. memory capacity je CPU	CPU xxxxH	CPU xxxxHL
Silver	4300	2666	6 TB		
Gold	5300	2933	6 TB	1,2 TB	4,5 TB
Gold	6300	3200	6 TB	1,2 TB	4,5 TB
Platinum	8300	3200	6 TB	1,2 TB	4,5 TB

# Information on memory installation

#### Product Datasheet | SP381459

16GB Computer memory for R182-N20



- Turn off the system
- Remove the plug of the power supply unit (if connected)
- Remove the battery, according to the user manual of the system
- Always ground yourself before touching electronic components
- Protect the memory module from static voltages:
  - Do not touch the gold pins of the memory module
  - Only touch the sides of the memory module
  - Use a grounding strap and/or ESD glove if possible

General installation instructions are supplied by E-Mail.



# Further memory options for Gigabyte R182-N20

8GB SP473617 DDR4 RDIMM (ECC 288 Pin DIMM PHS- Registered)	memory®
<i>5</i> ,	
16GB SP381459 DDR4 RDIMM (ECC 288 Pin DIMM PHS- Registered)	memory®
32GB SP381460 DDR4 RDIMM (ECC 288 Pin DIMM PHS- Registered)	memory®
64GB SP381461 DDR4 RDIMM (ECC 288 Pin DIMM PHS- Registered)	memory®
64GB SP381457 DDR4 LRDIMM (ECC 288 Pin DIMM PHS-I LR DIMM)	memory®
128GB SP470488 DDR4 LRDIMM (ECC 288 Pin DIMM PHS-I LR DIMM)	memory®
128GB SP473616 DDR4 LRDIMM (ECC 288 Pin DIMM PHS-I LR DIMM) 3DS	memory®
128GB SP381458 DDR4 RDIMM (ECC 288 Pin DIMM PHS- Registered) 3DS	memory®
256GB SP470490 DDR4 RDIMM (ECC 288 Pin DIMM PHS- Registered) 3DS	memory®
256GB SP470489 DDR4 LRDIMM (ECC 288 Pin DIMM PHS-I LR DIMM) 3DS	memory®

# PHS-memory® warranty

Every PHS-memory® is equipped with a 5-years-warranty of perfect operation. If the RAM module is defective or fails within 5 years of purchase when used properly, you will receive an appropriate RAM module free of charge. If a suitable memory module is no longer available, we will refund the purchase price.





#### Contact Information

PHS-electronic gmbh - www.phs-memory.es -Karl-Götz-Str. 5 97424 Schweinfurt Alemania Phone: +49 9721 784678 E-Mail: info@phs-memory.es Web: www.phs-memory.es

#### Product Datasheet | SP381459 16GB Computer memory for R182-N20



All information without guarantee. Technical changes and errors excepted. You can find current price information in our online shop at https://www.phs-memory.es